# **Lithium-ion Rechargeable Specification**

# Product name: LiFePO4 battery

# Product Item: LiFePO4 14500 6.4V 600mAh

	PREPARED	大学为
Specification Approved	CHECKED	年中山民均
	APPROVED	みった

Version No	Description of Revise	Date	Prepared
AO	New Publish	2020/06/11	Joan Li

#### SHENZHEN HIMAX ELECTRONICS CO., LTD.

Add:Building B, Nantong Avenue NO.5, Tongle Community, Baolong Street, Longgang Shenzhen China

Tel: 86 (0) 755-25629920 Fax: 86 (0) 755-25629925

www.himaxelectronics.com

www.himaxbattery.com

	DOC. NO. : HLFGB020A60-1115	
() HIMAX	REV. : A0	
SHENZHEN HIMAX ELECTRONICS CO.,LTD.	PAGE 2 OF 10	

# Content

1. ScopeP.3
2. ModelP.3
3. Reference standardP.3
4. SpecificationP.3~4
5. PCM ParameterP.4
6. Product Circuit diagram P.5
7. Electrical Performance & test condition
8. Mechanical Performance P.6
9. Cell Safety PerformanceP.7
10. Delivery/Packing/Storage and Shipment
11. Battery Pack FeatureP.8
12. Period of WarrantyP.9
13. WarningsP.9
14. Battery operation instruction P.91
15. Others P.10

DOC. NO. : HLFGB020A60-1115		
<b>REV. : A0</b>		
PAGE 3 OI	10	

## 1. Scope

This product specification describes HIMAX's LiFePO<sub>4</sub> battery. Please using the test methods that recommend in this specification. If you have any opinions or advice about the test items and methods, please contact us.

# 2. Model

Model: LiFePO4 14500 6.4V 600mAh

## 3. Reference standard

The standard reference GB/T18287-2013, UL1642 and CE61960 technology standards compiled.

# 4. Specification

Item		Rating	Note
Cell	Туре	LiFePO4 Battery	
	Cell Model	14500-600	
	Nominal Capacity	600mAh	Discharge: 0.5C Cut-off Voltage:2.5V
	Minimum Capacity	550mAh	Discharge: 0.5C Cut-off Voltage: 2.5V
	Nominal voltage	3.2V	
	Internal Impedance	≤60mΩ	
	Dimension	Max. 14.5x50.5mm	
	Weight	Approx.20.5g	
	Pack Method	2S1P	
	Nominal Capacity	600mAh	Discharge: 0.5C Cut-off Voltage:5V
	Minimum Capacity	550mAh	Discharge: 0.5C Cut-off Voltage: 5V
	Nominal Voltage	6.4V	
Battery	Energy	3.84Wh	
pack	Charge Voltage	7.3V	
	Discharge cut-off voltage	5V	
	Charge Method	CC/CV	
	Standard Charge Current	300mA	
	Max. Charge Current	600mA	
	Standard Discharge Current	300mA	

# 

SHENZHEN HIMAX ELECTRONICS CO., LTD.

DOC. NO. : HLFGB020A60-1115

REV. : A0

PAGE 4 OF 10


Max. Continues Discharge current	1200mA	
Cycle Life	2000 times	80% SOC
Internal Impedance	≤150mΩ	
Dimension	MAX.15.3*102mm	
Output Wire	UL1571 28AWG	
Output Connector	N/A	
Weight	Approx.40g	
Working Temperature Range	Charge: 0°C~45°C Discharge: -20°C~60°C	
Storage Temperature	-10°C~45°C	

# 5. PCM Parameter

No.	Item		Standard
1	Charge Current		/
2		Discharge Current	/
3		Balanced Current	/
5		Balanced Voltage	/
		Over-Charge Detect Voltage	/
4	Overcharge	Over-Charge Delay Time	/
		Over-Charge Reset Voltage	/
		Over-Discharge Detect Voltage	/
5	Over-discharge	Over-Discharge Delay Time	/
		Over-Discharge Reset Voltage	/
		Over-Current Detect Current	/
6	Over-current	Over-Current Delay Time	/
	Over-current	Reset	/
7	Short Circuit	Detect Status	/
7	Short Circuit	Reset	/
8	Resistance		/

DOC. NO. : HLFGB020A60-1115		
REV. : A0		
PAGE 5 OF 10		

## 6. Product Circuit diagram



#### 7. Electrical Performance & test condition

#### 7.1 Standard Test Condition

The battery shall be evaluated within 1 month from the arrival date.

Unless otherwise stated in these specifications, the following test shall be carried out in an ambient temperature of  $20\pm5^{\circ}$ C, relative humidity of  $65\pm20\%$ ,

Discharge capacity when the battery is discharged at 300mA to 5V after being standard charged. Five cycles are permitted for this test. The test shall be terminated at the end of the first cycle which meets the requirement.

#### 7.2 Testing Instrument or Apparatus

7.2.1 Dimension Measuring Instrument

The dimension measurement shall be implemented by instruments with equal or more precision scale of 0.01mm specified.

#### 7.2.2 Voltmeter and Ammeter

Voltmeters and ammeters shall be equal or more precision instruments of  $10K\Omega/V$  and  $0.01\Omega$ . 7.2.3 Impedance Meter

Impedance shall be measured by a sinusoidal alternating current method (1kHz LCR meter).

#### 7.3 Standard Charge

Standard charge means charging for 2.5hours using 7.3V/300mA charger.

#### 7.4 Standard Discharge

Standard discharge means discharging at 300mA down to 5V.

DOC. NO. : HLFGB020A60-1115

REV. : A0

PAGE 6 OF 10

#### 7.5 Electrical Performance

Item	Condition	Specification
Open-Circuit Voltage	The open-circuit voltage shall be measured within 24hours after standard charge.	≥6.4V
Battery Capacity	The discharge time at 300mA shall be measured after standard charge at $20\pm5^{\circ}C$ and rest 30mins.	≥92%
Cycle Life	The discharge time on standard discharge shall be measured after 2000 cycles of standard charge and discharge at 20±5°C.	≥80%
Charge(capacity) retention	The discharge time at 300mA shall be measured after standard charge and then storage at $20\pm5^{\circ}C$ for 28days.	≥95%
Temperature Characteristic 1	After standard charging at 20±5°C, laying the battery at 55°C for 2hours, then discharge at 300mA to 5V, record the discharge time.	≥85%
Temperature Characteristic 2	After standard charging at 20±5°C, laying the battery at -10°C for 4hours, then discharge at 300mA to 5V, record the discharge time .	≥50%

# 8. Mechanical Performance

ltem	Condition	Specification
Crush Test	A battery is to be crushed between two flat surfaces. The force for the crushing is to be applied by a hydraulic ram with a 32mm diameter piston. The crushing is to be continued until a pressure reading of 17.2mmPa is reached on the hydraulic ram, applied force of 13kN. Once the maximum pressure has been obtained it is to be released.	No fire No explosion
Drop Test	The battery has only two axes of symmetry in which case only two directions shall be tested. The battery is to be dropped from a height of 1 meter twice onto concrete ground.	No explosion, No fire, No smoke
Vibration	A full-charged battery is to be subjected to simple harmonic motion with an amplitude of 1.6mm total maximum excursion. The frequency is to be varied at the rate of 1 hertz per minute between 10 and 55 hertz. The cell shall be vibrated for 30 minutes per axis o XYZ axes.	No leakage No Fire No explosion

# 9. Cell Safety Performance

Item	Condition	Specification
Over charge	At $20\pm5^{\circ}$ C, charging battery with constant current 1C to voltage 4V, then with constant voltage 4V till current decline to 0.	No explosion, No fire
Over discharge	At 20±5°C, the cell are fully charged with standard charging method and standby at least 1 hour. The cell should be discharged at a current of 1C for 2.5h.	No explosion, No fire
Short-circuit	At $20\pm5^{\circ}$ C, The cells are fully charged with standard charging method and standby at least 1hour. Positive and negative terminal connect with wire (maximum load of $50$ m $\Omega$ ) to cause short circuit until its voltage is lower than 0.1V or cell temperature on the surface is back to room temperature $\pm 10^{\circ}$ C.	No explosion, No fire The temperature of the surface of the cell are lower than 150°C
Heating	Battery is heated in a circulating air oven at a rate of $5\pm2^{\circ}$ C per min to $130^{\circ}$ C, an then placed 30 mins at $130^{\circ}$ C.	No explosion, no fire

# 10. Delivery/Packing/Storage and Shipment

10.1 Approx. 30-70% charged before delivery, Shipment voltage: 6.2-6.6V.

## 10.2 Pre shipment inspection

The battery should be checked the voltage, resistance and the function of protective circuit before shipment.

#### 10.3 Packing and Shipping

10.3.1 The battery should be transported to the factory assembly, to pay special attention to the packing, in order to avoid transport stress.

10.3.2 The battery should be in a half state of charge packaging boxes for transport, in the transport process, prevent severe vibration, shock, extrusion, prevent the sun and rain, should be in automobile, train, ship, airplane and other forms.

## 10.4 Abnormal Condition

Do not use the battery when it's smell like abnormal cell electrolyte because of transport stress, sag, short circuit or any other.

	DOC. NO. : HLFGB020A60-1115			
	REV. : A0			
SHENZHEN HIMAX ELECTRONICS CO.,LTD.	PAGE 8 OF 10			

# 11. Battery Pack Feature

Item 1 2 3 4 5 HMS M File N			Connection Heat shrink PO4 14500 HLFGB020	( PVC		Signature		1
1 2 3 4 5	lodel	LiFel	Heat shrin	C PVC	blue			1
1 2 3 4			100404 CONSISTENCE - CONSISTEN	11812-0181 				1
1 2 3			100404 CONSISTENCE - CONSISTEN	11812-0181 		1		- 14 Jack
1 2			Connection Tab					100
1			Connection	Tab	8*4*0.12mm			2
1					exposed 30			
	11114	500	Cable		LFP 14500, 3.2V,600mAh,with PVC UL1571/28#AWG; red/yellow/black		pcs pcs	3
	IFR14	Number	Part Name Cell		Description	2V 600mAb with PVC	Unit	Quantit 2
BOM	MAX:15.		D. et l			3		
2				M	AX:102mm	30± 5mm	n UL1571/2	8#
1AX:1					1			-
MAX:15.3mm	-							=
F								
		)						
						$\frown$		

# **12.** Period of Warranty

The period of warranty is one year from the date of shipment. HIMAX guarantees to give a replacement in case of battery with defects proven due to manufacturing process instead of the customer abuse and misuse.

# 13. Warnings

To prevent the possibility of the battery from leaking, heating, fire, Please READ this specification carefully before usage and observe the following precautions:

◎When recharging, use the LiFePO4 battery charger specifically for that purpose.

◎ Do not strike battery with any sharp edge parts, such as Ni-tabs, pins and needles.

ODo not immerse the battery in water and seawater.

 $\bigcirc$  Do not use and leave the battery near a heat source as fire or heater.

 $\bigcirc$  Do not reverse the positive and negative terminals.

<sup>O</sup>Do not connect the battery to an electrical outlet.

 $\bigcirc$  Do not discard the battery in fire or heat it.

◎The battery tabs are not so stubborn especially for aluminum tab. Do not bend tab.

 $\bigcirc {\sf O} {\sf Do}$  not short-circuit the battery by directly connecting the positive and negative terminal with metal object.

 $\bigcirc$  Do not transport and store the battery together with metal objects such as necklaces, hairpins etc.

◎ Do not knock or throw, trampling battery etc.

 $\bigcirc$  Do not directly solder the battery and pierce the battery with a nail or other sharp object.  $\bigcirc$  Do not solit the battery without permission

ODo not split the battery without permission.

## 14. Battery operation instruction

#### 14.1 Charging

Charging current: Do not surpass the biggest charging current which in this specification.

Charging voltage: Do not surpass the highest voltage which in this specification.

Charge temperature: The charge temperature is in according to this specification.

#### 14.2 Discharging

Discharge current: Do not surpass the max discharge current which in this specification. Discharging with a higher current may result in the capacity fade and over-heat. Discharge temperature: The discharge temperature is in according to this specification.

#### 14.3 Over-discharges

After the short time excessively discharges charges immediately cannot affect the use, but the long time excessively discharges can cause the battery the performance, battery function losing. The battery long-term has not used, has the possibility to be able to be at because of its automatic flashover characteristic certain excessively discharges the condition, for prevented excessively

	DOC. NO. : HLFGB020A60-1115			
	REV. : A0			
SHENZHEN HIMAX ELECTRONICS CO.,LTD.	PAGE 10 OF 10			

discharges the occurrence, the battery should maintain the certain electric quantity.

#### **14.4 Storing the Batteries**

The battery should store in the product specification book stipulation temperature range. If has surpasses above for 3 months the long time storage, suggested you should carry on additional charge to the battery.

14.5 Please do not continuously charge the battery over 4hours.

#### 15. Others

◎ The customer is requested to contact HIMAX in advance, if and when the customer needs other applications or operating conditions than those described in this document. Additional experimentation may be required to verify performance and safety under such conditions.

◎HIMAX will take no responsibility for any accident when the battery is used under other conditions than those described in this Document.

◎HIMAX will inform, in a written form, the customer of improvement(s) regarding proper use and handing of the battery, if it is deemed necessary.